

OpenText appliances for security operations

Shorten time-to-benefits, improve ongoing performance for threat detection and response, and simplify log management and compliance.

“I liken OpenText Enterprise Security Manager to a Ferrari. It takes you a little while to get to know all its abilities, but once you do, it is the most powerful security solution you will find.”

Security Information Analyst,
Major Healthcare Provider

New appliances for OpenText™ Enterprise Security Manager, OpenText™ Security Logger, and connectors offer faster speeds, more storage, and enhanced security for your organization. In addition, new appliances for Security Log Analytics, database, and storage are also being introduced. Discover why you should take advantage of OpenText's upgraded appliances, built to address the needs of a Next-Gen SOC.

With new appliances, you can:

- Collect more data with the Logger appliance and gain nearly 2x capacity over older Gen 10 appliances.
- Scale up to 2.5 petabytes of storage with the S8000 storage appliance.
- Scale up easily to support more EPS than the previous Gen10 servers.
- Speed up analysis with faster processors and memory in our new appliances.
- Simplify new X-Series deployments with EN8000 No hassle plug-n-play SLED enclosure.
- Monitor faster network with a 25Gb network card standard.
- Future-proof your investments with these growth-ready appliances.
- Improve security with iDRAC version 9's advanced security.

	Logger L8000 Appliance	Security Log Analytics R8000 Appliance (All-In-One)
Appliance family	Dell R7615	Dell R7615
Processor	AMD EPYC 9224 2.5GHz, 24C/48T; 64M Cache	AMD EPYC 9224 2.5GHz, 24C/48T; 64M Cache
Memory	192 GB RDIMM (12×16 GB 5600MT/s Single Rank)	192 GB RDIMM (12×16 GB 5600MT/s Single Rank)
Storage	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 64TB 5×16TB SAS FIPS SED-140 SED 7.2K 512e 3.5" Hot Plugin RAID 5 • Total Event Storage – 48 TB 	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 48TB 4×16TB SAS FIPS SED-140 SED 7.2K 512e 3.5" Hot Plugin RAID 5 • 7.2TB 4×2.4TB 10K RPM SAS 12Gbps 512e 2.5in, FIPS SED-140 SED, RAID 5
OS	Red Hat Enterprise Linux 8.8 64-bit	Red Hat Enterprise Linux 9.2 64-bit
Networking	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter • Broadcom 5720 Dual Port 1 GbE Optional LOM 	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter • Broadcom 5720 Dual Port 1 GbE Optional LOM
Chassis	2U	2U
Power	Dual, Hot-Plug, Power Supply, 1100W MM (100-240V) Titanium, Redundant (1+1)	Dual, Hot-Plug, Power Supply, 1100W MM (100-240V) Titanium, Redundant (1+1)
EPS rating	30K EPS Continuous	5K EPS Continuous

	Security Log Analytics R8100 Appliance (All-In-One)	Storage S8000 Appliance (4 unit minimum, 20 maximum)
Appliance family	Dell R7615	Dell R7615
Processor	AMD EPYC 9224 2.5GHz, 24C/48T; 64M Cache	AMD EPYC 9224 2.5GHz, 24C/48T; 64M Cache
Memory	384 GB RDIMM (12×32 GB 5600MT/s Dual Rank)	192 GB RDIMM (12×16 GB 5600MT/s Single Rank)
Storage	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 160TB 12×16TB SAS FIPS SED-140 SED 7.2K 512e 3.5" Hot Plugin RAID 50-2 • 7.2TB 4×2.4TB 10K RPM Self-Encrypting SAS 12Gbps 512e 2.5in, FIPS SED-140 SED, RAID 5 	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 192TB 12×16TB SAS FIPS SED-140 SED 7.2K 512e 3.5" Hard Drive (JBOD) • 7.68TB 2×3.84TB SSD up to SAS 24 Gbps FIPS-140 RI 512e 2.5in Flex Bay, AG
OS	Red Hat Enterprise Linux 9.2 64-bit	Red Hat Enterprise Linux 9.2 64-bit
Networking	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter • Broadcom 5720 Dual Port 1 GbE Optional LOM 	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter • Broadcom 5720 Dual Port 1 GbE Optional LOM
Chassis	2U	2U
Power	Dual, Hot-Plug, Power Supply, 1100W MM (100-240V) Titanium, Redundant (1+1)	Dual, Hot-Plug, Power Supply, 1100W MM (100-240V) Titanium, Redundant (1+1)
EPS rating	20K EPS Continuous	100K EPS Continuous

The new X-Series appliances are powered by AMD EPYC 9224 2.5GHz 24C/48T Processor with 64M Cache DDR5-4800. They also take advantage of the Dell C6600-B Enclosure, a 2U4N compute sled. It is designed to run complex workloads using highly scalable memory and capacity, I/O bandwidth and network options.

	EN8000	Connector C8200 Appliance
Appliance family	Dell 6600-B Enclosure	Dell PowerEdge 6615 SLED
Processor	N/A	AMD EPYC 8224P 2.5GHz, 24C/48T; 64M Cache
Memory	N/A	96GB RDIMM (6×16 GB 5600MT/s Single Rank)
Storage	N/A	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 7.2TB 4×2.4TB 10K RPM Self-Encrypting SAS 12Gbps 512e 2.5in Hot-plug Hard Drive, FIPS SED140 SEC, RAID 5
OS	N/A	Red Hat Enterprise Linux 9.2 64-bit
Networking	N/A	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter
Chassis	2U	2U
Power	240V, only support 2 SLEDs at 120V	Hot-Plug, Power Supply, 2400W (1+1) provided by the EN8000 enclosure
Connector		32 Connectors

	Database Compute DB8400 Appliance	Worker Node W8300 Appliance
Appliance family	Dell PowerEdge 6615 SLED	Dell PowerEdge 6615 SLED
Processor	AMD EPYC 8224P 2.5GHz, 24C/48T; 64M Cache	AMD EPYC 8224P 2.5GHz, 24C/48T; 64M Cache
Memory	192GB RDIMM (6×32 GB 5600MT/s Dual Rank)	192GB RDIMM (6×32 GB 5600MT/s Dual Rank)
Storage	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 23TB 4×7.68 SSD up to SAS 24Gbps FIPS-140 RI 512e 2.5in Hot-Plug, AG, RAID 5 	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 7.2TB 4×2.4TB 10K RPM Self-Encrypting SAS 12Gbps 512e 2.5in Hot-plug Hard Drive, FIPS SED140 SEC, RAID 5
OS	Red Hat Enterprise Linux 9.2 64-bit	Red Hat Enterprise Linux 9.2 64-bit
Networking	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter 	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter
Chassis	2U	2U
Power	Hot-Plug, Power Supply, 2400W (1+1) provided by the EN8000 enclosure	Hot-Plug, Power Supply, 2400W (1+1) provided by the EN8000 enclosure

	ESM E8400 Appliance	ESM EC8300 Appliance
Appliance family	Dell PowerEdge 6615 SLED	Dell PowerEdge 6615 SLED
Processor	AMD EPYC 8224P 2.5GHz, 24C/48T; 64M Cache	AMD EPYC 8224P 2.5GHz, 24C/48T; 64M Cache
Memory	192GB RDIMM (6×32 GB 5600MT/s Dual Rank)	192GB RDIMM (6×32 GB 5600MT/s Dual Rank)
Storage	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 23TB 4×7.68 SSD up to SAS 24Gbps FIPS-140 RI 512e 2.5in Hot-Plug, AG, RAID 5 	<ul style="list-style-type: none"> • Boot - 480 GB (2×480 GB SSD NVMe for OS / App RAID 1) • 7.2TB 4×2.4TB 10K RPM Self-Encrypting SAS 12Gbps 512e 2.5in Hot-plug Hard Drive, FIPS SED140 SEC, RAID 5
OS	Red Hat Enterprise Linux 9.2 64-bit	Red Hat Enterprise Linux 9.2 64-bit
Networking	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter 	<ul style="list-style-type: none"> • Broadcom 57416 Dual Port 10GbE BASE-T Adapter • Broadcom 57414 Dual Port 10/25GbE SFP28 Adapter
Chassis	2U	2U
Power	Hot-Plug, Power Supply, 2400W (1+1) provided by the EN8000 enclosure	Hot-Plug, Power Supply, 2400W (1+1) provided by the EN8000 enclosure

Resources

[OpenText Enterprise Security Manager](#) ›

[OpenText Security Log Analytics](#) ›

“We use many disparate data sources, all producing events that need to be logged. With OpenText Secure Open Data Platform Connectors, we collect information from the entire environment, giving us a full picture at any point.”

SANDI Bižal
Security Officer
Adriatic Slovenia